

Risalto Led DMX Chart (5/1 ch)

channel		function	tune of control	effect	dooi	desimal					
5 ch	1ch	iuilction	type of control	eneci	deci	decimal			pecentage		
1	1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0 -	255	0%	-	100%		
2	-	spare channel	step	no effect	0 -	255	0%	F	1009		
3	-	dimmer fine	proportional	fine dimmer control 16 bit	0 -	255	0%	-	1009		
		strobe effect	step	no effect	0 -	9	0%	Ī	4%		
			proportional	variable speed strobing effect, from slow to fast	10 -	57	4%	Ħ	22%		
			step	stop strobe	58 -	59	23%	-	23%		
			proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60 -	108	24%	-	42%		
4			step	stop strobe	109 -	110	43%	-	43%		
	-		proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111 -	159	44%	-	62%		
			step	stop strobe	160 -	161	63%	-	63%		
			proportional	random strobe effect with variable speed from slow to fast	162 -	207	64%	-	819		
			step	stop strobe	208 -	209	82%	H	829		
			proportional	random strobe effect with variable speed from slow to fast	210 -	255	82%	-	100		
		special function		no effect	0 -	9	0%	-	4%		
			aton	600 Hz	10 -	84	4%	-	339		
			step	fan at low-noise speed	85 -	96	33%	-	389		
				fan at auto speed	97 -	108	38%	-	429		
			proportional	fan speed control	109 -	120	43%	-	47°		
				fan at studio mode	121 -	133	47%	-	529		
				LCD display off	134 -	185	53%	-	739		
				LCD display on	186 -	199	73%	-	789		
5	-			LED control frequency tuning 1000Hz	200 -	205	78%	-	809		
				LED control frequency tuning 3000Hz	206 -	211	81%	-	839		
			aton	LED control frequency tuning 6000Hz	212 -	217	83%	-	859		
			step	LED control frequency tuning 8000Hz	218 -	223	85%	-	879		
				LED control frequency tuning 10000Hz	224 -	229	88%	-	909		
				LED control frequency tuning 12000Hz	230 -	235	90%	-	929		
				LED control frequency tuning 14000Hz	236 -	241	93%	-	959		
				LED control frequency tuning 16000Hz	242 -	247	95%	-	979		
				LED control frequency tuning 19000Hz	248 -	255	97%	-	100		
		alto Led		Table name: DMX 512 functions			n: 1.22				